CXKEY - CX Keytag Ordering Guide

Standard Part No.: CXKEY-SSSS-0000
Description: 125 kHz, printed Indala logo on front side, printed strip for marking on back side.

CXKEY S S S S 0000

BASE NUMBER
PROGRAMMING
FRONT GRAPHICS
BACK GRAPHICS
MARKING POSITION
CUSTOM FILE NO.

BASE NUMBER

CXKEY Keytag style proximity card

PROGRAMMING

S = Standard Programmed, Low Frequency 125 kHz – **CASI-RUSCO** 12-digit format with no external marking number. Marking of "CXdddy" is standard.

M = Sequential Matching. Programmed, Low Frequency 125 kHz – **CASI-RUSCO** 12-digit format with matching (6-digit) external marked number. **Note**: the programmed internal number of a CASI card is a 12-digit ID number, example 151234123456. When Matching external numbers are requested, only the last six digits of the 12-digit encoded number are printed on the card along with the CX designation and a date code. For the sample number shown, the marking would be "CXdddy 123456" A cross reference of marking to encoded number will be provided with the order in .txt (text) format

Q = Sequential Non Matching. Programmed, Low Frequency 125 kHz – **CASI-RUSCO** 12-digit format with a sequential 6-digit external marked number with a customer specified start number. (For example, if 2000 cards are ordered with a starting marking number of 425000, the marking would start at "CXdddy 425000" and end at "CXdddy 426999") A cross reference of marking to encoded number will be provided with the order in .txt (text) format.

FRONT GRAPHICS

S = Standard (printed Indala logo)
C = Custom (Artwork on file or new)

BACK GRAPHICS

S = Standard (no logo, printed strip for marking)
C = Custom (Artwork on file or new)

MARKING POSITION

(Standard Marking (the CX designation and a date code), is used unless otherwise specified)
Note: Inkjet marking is surface printed and, therefore is not to be considered permanent. Most Keytag marking will be with Laser etching which is permanent in most applications.

S = Standard (back side on printed strip)

CUSTOM FILE NUMBER (4 Characters – Factory Assigned)

0000 = No Artwork
(Call your Customer Service Representative for new artwork)

© 2008 HID Global Corporation. All rights reserved.